Toll Free: (800) 658-0567 Phone:(308) 381-4000 Fax: (308) 381-2801



# **MINITOR V**

# **FEATURES:**

# Wide and Narrow-Band Programmable Channel Spacing

VHF and UHF models only

### **Expanded Stored Voice**

Records up to 8 minutes of voice message for playback

#### **Silent Scan (Dual Frequency model)**

Scans both channels silently, alerts on either channel

## **Priority Scan (Duel Frequency model)**

Plays all traffic on Channel 2, alerts on Channel 1

## Speaker/Earphone Jack

#### 12 Alert Tones Per Channel

Supports 8 two-tone pairs and 4 individual long-tone alerts

#### **Programmable Music Alerts**

Supports 10 different musical alerts

#### **Function Mode Announcement (stored voice option)**

Announces programmed operating mode



The Motorola MINITOR V pager is ideal for fire departments as well as businesses and other organizations that must react quickly in times of emergency.

# Specification:

Audio Output 94 dB @ 12"

Battery 3.6V NiMH

Channel Spacing Wide & Narrow Band

Frequency Lowband (33-49 MHz), VHF (143-174 MHz), UHF (406-430

and 450-512)

Operating Temperature -30°C to +50°C

Paging Protocol Two-Tone

Selectivity 65 dB

Sensitivity 3.0 to 5.5 uV/m

Spurious Image Rejection 55 dB

Type Voice Only